

Product No.		DA-72-12	DA-72-24				
Output	DC voltage	12V	24V				
	Rated Current	6A	3A				
	Current Range	0-6A	0-3A				
	Rated Power	72W	72W				
	Ripple and Noise(Max)Note.2	150mVp-p	240mVp-p				
	Voltage adjustment						
	Voltage Accuracy Note3	±1%	±1%				
	Linear Adjustment Note4	±0.5%	±0.5%				
	Load Adjustment Note5	±0.5%	±0.5%				
	Start and rise time	1000ms,30ms/230VAC 1000ms,30ms/110V					
	Hold time (Typ)	50ms/230VAC 10ms/115AC					
Input	Voltage range	100-240V					
	Frequency range	50-60Hz					
	Efficiency (Typ)	80%	82%				
	AC current (Typ)	0.8A/90V 0.33A/220V					
	Surge current (Typ)	Cold Start: 65A/230VAC					
	Current leak	<2mA/240VAC					
Protection	Overload -	>105% rated output power					
		Protection type : Hiccup mode, recovers automatically after fault condition is removed					
	Overvoltage						
	Overheat -						
Environment	Working temp.	-20 \sim +60 $^{\circ}\mathbb{C}$ (Refer to the tenuation curve)					
	Working humidity	$20 \sim 90\%$ RH, without condense					
	Storage temp & hmdty	-40~+80℃					
	Temp. coefficient	±0.03%/°C (0~50°C)					
	Vibration proof	$10{\sim}500$ HZ,5G 10 min / cycle $_{ m J}$ X $_{ m V}$ X axes 60 min each					
	Safety regulation	GB195110.1-2004/IEC61347-1:2003 CE(EMC+LVD)					
Safety reg. & EMC (Note.6)	Voltage proof	I/P-O:1.5KVAC I/P-FG:1.5KVAC O/P-FG:0.5KVAC					
	insulation resistance	I/P-O/P, I/P-FG,O/P-FG:100M Ohms/500VDC/25°C/70% RH					
	EMC irradiation	EN 55032A:2006;EN61000-3-2:1995+A2:2005					
	EMC disturbance proof	EN 61000-3-2:2006;					
	Dimensions	120*53*31mm					
	Packing	0.25Kg/PCS;50PCS/12.5kg					
Notes:	1. All parameters NOT specially mentinoed are measured at 230VAC input, rated load and 25°C of ambient temperature.						
	2.Ripple and noise are measured at 20MHz bandwidth by using a 12" twisted pair-wire terminated with a 0.1μ F and a 47 μ F parallel capacitor.						
	3.Accuracy: including preset errors, linear adjustment rate and load adjustment rate.						
	4.Linear adjustment: taken under rated load from low voltage to high voltage.						
	5.Load adjustment: taken under 0~100% of rated load.						
	6. The power supply is taken as part of the whole system, and needs to be confirmed with final equipment for EMC.						



